

Connection

1. Connect the telephone line cord to a telephone network wall socket.
2. For Australia/New Zealand only: Ensure that the recall button timing switch underneath the telephone is correctly set (100 ms UK/EU/AUS or 300 ms France/Portugal or 600 ms NZ).


IMPORTANT!

Use the telephone line cord supplied, an existing line cord from a previous phone may not be compatible.


Mute button

Press and hold  to disable the handset microphone, release  to reconnect the microphone.

Redial function

When the number dialled is engaged or if you wish to redial the last number dialled, lift the handset and press .

Volume control

The handset earpiece volume may be adjusted using  located on the side of the telephone.




Ringer


The ringer volume and melody can be selected using the switches located on the underside of the telephone:

 Ringer volume

 Ringer type

Recall

Access to additional network services such as “Call Waiting” can be gained by using the recall button . Example: when the call waiting tones are heard, press , listen for the dial tone, then press 2. Please note that some networks require only the  button to be pressed, contact your network operator for more services information.

If this product is connected to a business PBX system, press the recall button  followed by the extension number to transfer a call. The standard setting is 100 ms for UK/Australia and 600 ms for New Zealand.

Troubleshooting

Check that the line cord is undamaged. Disconnect any additional equipment, extension cords and other telephones. If the problem is resolved, the fault is with the other equipment. Test the equipment on a known working line. If the product works then the fault is probably with the line. Please inform your local network operator. If you are still experiencing difficulties, contact Doro or the place of purchase.


EU Declaration of conformity



Hereby, Doro declares that the equipment type Doro 909c is in compliance with Directives: 2014/53/EU and 2011/65/EU. The full text of the EU declaration of conformity is available at the following internet address:

www.doro.com/dofc

Guarantee

This product is guaranteed for a period of 24 months from the date of purchase. Proof of purchase is required for any service or support required during the guarantee period. This guarantee shall not apply to a fault caused by an accident or a similar incident or damage, liquid ingress, negligence, abnormal usage or any other circumstances on the purchaser's part. Furthermore, this guarantee shall not apply to a fault caused by a thunderstorm or any other voltage fluctuations. This guarantee does not in any way affect your statutory rights. (As a matter of precaution, we recommend disconnecting the telephone during a thunderstorm.)

Wall mounting**Australia and New Zealand**

Products permitted for connection to the telephone network are marked with  in Australia and  TELEPERMIT in New Zealand. These marks indicate the products comply with the regulations and can be legally connected in the country of purchase.

If you believe this product is malfunctioning, please refer to the relevant section and/or consult the troubleshooting guide in this manual to ensure that you have followed the instructions carefully. As an alternative you can visit our web site for FAQ's or send an e-mail for a prompt reply.

Guarantee

This product is guaranteed for a period of 12 months from the date of purchase.

Should you experience difficulties with the product, please contact us for assistance. If the product is then found to be faulty you will be asked to return it directly to us with a copy of the purchase receipt. This guarantee shall not apply to a fault caused by an accident or a similar incident or damage, liquid ingress negligence, abnormal usage, not reasonably maintained or any other circumstances on the purchaser's part. Furthermore, this guarantee shall not apply to a fault caused by a thunderstorm or lightning, excessive or any other voltage fluctuations or faults on the telephone line. (As a matter of precaution, we recommend disconnecting the telephone during a thunderstorm).

This guarantee does not affect your statutory rights.

AUSTRALIA

DORO Australia Pty Ltd
PO Box 6760
Baulkham Hills BC NSW 2153
Australia

NEW ZEALAND

Atlas Gentech (NZ) Limited
Private Bag 14927
Panmure
Auckland
New Zealand

Consumer Support

Ph: Ph: 1300 885 023

Fax: (02) 8853-8489

Email: support@doro.com.au

Web site: www.doro.com.au

Consumer Support

Ph: 0900-500-25 (Toll Call)

Fax: (09) 574-2722

Email:

support@atlasgentech.co.nz

REN (RN for New Zealand)

The REN (Ringer Equivalence Number) or (RN) is of significance only if you wish to connect more than 1 telephone to your telephone line. A standard telephone line has a maximum REN capacity of 3 (RN of 5). It is possible to connect 3 devices with a REN of 1 (RN of 1) with no degradation to the product's performance. Exceeding this limit may cause the volume of the ringer in any phone to decrease or not ring at all.

ALL PRODUCTS

The grant of a Telepermit for any item of terminal equipment indicates only that Telecom has accepted that the item complies with the minimum conditions for connection to its network. It indicates no endorsement of the product by Telecom, nor does it provide any sort of warranty. Above all, it provides no assurance that any item will work correctly in all respects with another item of Telepermitted equipment of a different make or model, nor does it imply that any product is compatible with all of Telecom's network services.

This equipment shall not be set to make automatic calls to the Telecom “111” Emergency Service.

This equipment may not provide for the effective hand-over of a call to another device connected to the same line.

This equipment should not be used under any circumstances that may constitute a nuisance to other Telecom Customers.



doro 909c

WEEE

English (GB): Correct disposal of this product

(Waste Electrical & Electronic Equipment)

(Applicable in countries with separate collection systems)

This marking on the product, accessories or manual indicates that the product and its electronic accessories (e.g. charger, headset, USB cable) should not be disposed of with other household waste.

To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate these items from other types of waste and recycle them responsibly to promote the sustainable reuse of material resources. Household users should contact either the retailer where they purchased this product, or their local government office, for details of where and how they can take these items for environmentally safe recycling. Business users should contact their supplier and check the terms and conditions of the purchase contract. This product and its electronic accessories should not be mixed with other commercial wastes for disposal. This product is RoHS compliant.



Correct disposal of batteries in this product

(Applicable in countries with separate collection systems)

The marking on the battery, manual or packaging indicates that the battery in this product should not be disposed of with other household waste.

Where marked, the chemical symbols Hg, Cd or Pb indicate that the battery contains mercury, cadmium or lead above the reference levels in EC Directive 2006/66.



English

Version 2.0

www.doro.com

